

General Disclaimer

One or more of the Following Statements may affect this Document

- This document has been reproduced from the best copy furnished by the organizational source. It is being released in the interest of making available as much information as possible.
- This document may contain data, which exceeds the sheet parameters. It was furnished in this condition by the organizational source and is the best copy available.
- This document may contain tone-on-tone or color graphs, charts and/or pictures, which have been reproduced in black and white.
- This document is paginated as submitted by the original source.
- Portions of this document are not fully legible due to the historical nature of some of the material. However, it is the best reproduction available from the original submission.

366
EB-67-2001-U

PREDICTING PLL THRESHOLD BEHAVIOR
WITH SINUSOIDAL AND GAUSSIAN MODULATION
USING THE RICE - RIDGEWAY CRITERIA

by

Frank J. Loch



FACILITY FORM 602	N70 - 35870	
	(ACCESSION NUMBER)	(THRU)
	9	1
	(PAGES)	(CODE)
	TMX-65064	07
	(NASA CR OR TMX OR AD NUMBER)	(CATEGORY)

Information Systems Division
Systems Analysis Branch
February 21, 1967

The equation derived by S. O. Rice in his classic paper relating $(S/N)_o$ to $(S/N)_{in}$ is as follows:

$$S_o/N_o = \frac{3\rho B_{IF}^3 (2f_a)^{-3}}{\rho\sqrt{3} (1 - \text{erf}\sqrt{\rho}) \left(\frac{B_{IF}}{f_a}\right)^2 + 1} \quad (1)$$

This equation is valid for the case where $\frac{\Delta f}{f_a} > 5$, and the predetection bandwidth B_{IF} is given by:

$$B_{IF} = 2\Delta f$$

However, for the cases of interest $\frac{\Delta f}{f_a} < 5$ and the contribution of the peak modulating frequency f_a must be considered. Therefore, $B_{IF} = 2[\Delta f + f_a]$ and Equation (1) becomes:

$$S_o/N_o = \frac{\frac{3}{2} \rho \frac{B_{IF}}{f_a} \left(\frac{\Delta f}{f_a}\right)^2}{\rho\sqrt{3} \left(\frac{B_{IF}}{f_a}\right)^2 (1 - \text{erf}\sqrt{\rho}) + 1} \quad (2)$$

Equations (1) and (2) were derived on the assumption that the input signal + noise is given by:

$$\text{Input} = Q \cos(\omega_c t - \frac{A}{\omega_s} \cos \omega_s t) + I_N \quad (3)$$

and

$$I_N = I_C \cos \omega_c t - I_S \sin \omega_c t \quad (4)$$

where I_C and I_S are the in-phase and quadrature phase components of the noise I_N with respect to the carrier frequency $\frac{\omega_c}{2\pi}$.

Also, the assumption that the signal amplitude $A = 0$ was made so that Equation (3) reduces to:

$$\text{Input} = Q \cos \omega_c t + I_N \quad (5)$$

The generalized version of Equation (2) can be written as:

$$S_o/N_o = \frac{\frac{3}{2} \rho \frac{BIF}{f_a} \left(\frac{\Delta f}{f_a}\right)^2}{\rho \left(\frac{BIF}{f_a}\right)^2 K \left(\frac{N^+}{BIF}\right) + C} \quad (6)$$

where N^+ is the number of positive clicks per second, and K is a constant.

By referring to Equation (2) we can see that for the unmodulated case, where the signal amplitude is 0, $K = 12$, and

$$\frac{N^+}{BIF} = (1 - \text{erf}\sqrt{\rho}) \left(\frac{1}{4\sqrt{3}}\right) \quad (7)$$

This expression for $\frac{N^+}{BIF}$ is obtained from Rice's derivation of N^+ ;

$$N^+ = \frac{r}{2} (1 - \text{erf}\sqrt{\rho}) \quad (8)$$

where r is defined as being the radius of gyration of the power spectrum $w(f)$ about its axis of symmetry, $f = f_c$.

$$r = \frac{1}{2\pi} \left(\frac{b_2}{b_0}\right)^{1/2} \quad (9)$$

$$b_0 = \overline{I_N} = \overline{I_C} = \overline{I_S} = \int_0^{\infty} w(f) df = \int_0^{\infty} 2w(f_c + f) df \quad (10)$$

$$b_2 = (2\pi)^2 \int_0^{\infty} (f - f_c)^2 w(f) df \quad (11)$$

Assuming a rectangular filter of bandwidth B_{IF} cps centered on f_c , then it follows that:

$$w(f) = w_0 \text{ for } f_c - B_{IF}/2 < f < f_c + B_{IF}/2$$

and

$$w(f) = 0 \text{ elsewhere.}$$

$$b_0 = \int_{f_c - B_{IF}/2}^{f_c + B_{IF}/2} w_0 df = w_0 [f_c + B_{IF}/2 - f_c + B_{IF}/2] = w_0 B_{IF} \quad (12)$$

$$b_2 = 4\pi^2 \int_{f_c - B_{IF}/2}^{f_c + B_{IF}/2} w_0 (f - f_c)^2 df = 4\pi^2 w_0 \frac{(f - f_c)^3}{3} \Bigg|_{f_c - B_{IF}/2}^{f_c + B_{IF}/2}$$

$$b_2 = \frac{4\pi^2}{3} w_0 [(f_c + B_{IF}/2 - f_c)^3 - (f_c - B_{IF}/2 - f_c)^3]$$

$$= \frac{4}{3} \pi^2 w_0 [(B_{IF}/2)^3 - (-\frac{B_{IF}}{2})^3] = \frac{4}{3} \pi^2 w_0 (\frac{1}{2})^3 [2B_{IF}^3]$$

$$= \frac{4\pi^2 w_0 (2)}{(3)(8)} B_{IF}^3 = \frac{\pi^2 w_0 B_{IF}^3}{3} \quad (13)$$

$$\therefore r = \frac{1}{2\pi} \left(\frac{b_2}{b_0} \right)^{1/2} \quad (14)$$

$$= \frac{1}{2\pi} \frac{\left(\frac{\pi^2 w_0 B_{IF}^3}{3} \right)^{1/2}}{(w_0 B_{IF})^{1/2}} = \frac{1}{2\pi} \left(\frac{w_0}{w_0} \right)^{1/2} B_{IF} \frac{1}{\sqrt{3}}$$

$$r = \frac{B_{IF}}{2\sqrt{3}} \quad (15)$$

$$\therefore N^+ = \frac{r}{2} (1 - \operatorname{erf} \sqrt{\rho}) = \frac{B_{IF}}{4\sqrt{3}} (1 - \operatorname{erf} \sqrt{\rho}) \quad (16)$$

and

$$\frac{N^+}{B_{IF}} = \frac{1}{4\sqrt{3}} (1 - \operatorname{erf} \sqrt{\rho}) \quad (17)$$

For the case of sinusoidal modulation the expression for the number of positive clicks per second, as derived by Rice, is as follows:

$$N^+ \approx \frac{A}{2\pi} \frac{e^{-\rho}}{\pi} + \frac{r e^{-\rho}}{(4\pi \rho)^{1/2}} e^{-a\rho} I_0(a\rho) \quad (18)$$

where

$$a = \frac{(A/2\pi)^2}{2r^2} = \left[\frac{\operatorname{rms}(\phi'/2\pi)}{r} \right]^2 \quad (19)$$

and

$$\phi' = A \sin \omega_s t \quad (20)$$

A maximum frequency deviation is desired which will make the carrier fill up the entire rectangular input bandwidth. This is accomplished by letting

$$A/2\pi = B_{IF}/2 \quad (21)$$

Therefore,

$$a = \frac{(B_{IF}/2)^2}{2r^2} \quad (22)$$

and

$$N^+ \sim \frac{B_{IF}}{2} \frac{e^{-\rho}}{\pi} + \frac{r e^{-\rho}}{(4\pi\rho)^{1/2}} e^{-a\rho} I_0(a\rho) \quad (23)$$

Since $r = \frac{B_{IF}}{2\sqrt{3}}$, we can write:

$$N^+ \sim \frac{B_{IF} e^{-\rho}}{2\pi} + \frac{B_{IF} e^{-\rho}}{(48\pi\rho)^{1/2}} e^{-a\rho} I_0(a\rho) \quad (24)$$

$$\therefore \frac{N^+}{B_{IF}} \sim \frac{e^{-\rho}}{2\pi} + \frac{e^{-\rho} (1+a)}{(48\pi\rho)^{1/2}} I_0(a\rho) \quad (25)$$

Further simplification can be made by noting that:

$$a = \frac{B_{IF}^2/4}{2r^2} = \frac{B_{IF}^2/4}{2B_{IF}^2/12} = \frac{3}{2} \quad (26)$$

Finally we have,

$$\frac{N^+}{B_{IF}} \approx \frac{e^{-\rho}}{2\pi} \left[1 + \left(\frac{\pi}{12\rho} \right)^{1/2} e^{-3\rho/2} I_0\left(\frac{3\rho}{2}\right) \right] \quad (27)$$

The exact expression for $\frac{N^+}{B_{IF}}$ is plotted in Rice's classic paper on noise in FM receivers. Since the graph of the expression is extremely linear down to a carrier to noise ratio $\rho = .5$, a simplified but accurate equation can be derived which can replace Equation (27) for use in a computer program, etc.

Referring to Figure IV, page 406 of Rice's paper Noise in FM Receivers, let:

$$y = K X + b \quad (28)$$

$$y = \log \frac{N^+}{B_{IF}} \quad (29)$$

$$\log \frac{N^+}{B_{IF}} = K X + b \quad (30)$$

$$X = \rho \quad (31)$$

$$(y_1 \ x_1) = (.003, 4)$$

$$(y_2 \ x_2) = (.06, 1)$$

$$\log (.003) = 4K + b$$

$$\underline{-\log (.06) = -K - b}$$

$$\log (.003) - \log (.06) = 3K$$

$$3K = \log \left(\frac{.003}{.06} \right) = \log .05 = \log \frac{1}{20} = -1.3$$

$$\underline{\therefore K = -.434}$$

$$\log \left(\frac{N^+}{B_{IF}} \right) = -.434 \rho + b$$

$$\log (.06) = -.434 + b$$

$$-1.22 = -.434 + b$$

$$b = -.788$$

$$\therefore \log \left(\frac{N^+}{B_{IF}} \right) = -(.434 \rho + .788) \quad (32)$$

or

$$\frac{N^+}{B_{IF}} = +\log^{-1}(.434 \rho + .788) \quad (33)$$

Referring to Equation (6), for the case of sinusoidal modulation, we can write:

$$S_o/N_o = \frac{3/2 \rho \frac{B_{IF}}{f_a} \left(\frac{\Delta f}{f_a} \right)^2}{+12 \rho \left(\frac{B_{IF}}{f_a} \right)^2 \log^{-1}(.434 \rho + .788) + c} \quad (34)$$

where

$$c = [J_0^2 + J_5^2 + 2(J_1^2 + J_2^2 + J_3^2 + J_4^2)] \quad (35)$$

For the case of a signal ϕ' having Gaussian statistics with zero average and variance $\overline{\phi'^2}$ the expression for N^+ as derived by Rice is as follows:

$$N^+ = N^- \sim r e^{-\rho} \left(\frac{1 + 2 a \rho}{4 \pi \rho} \right)^{1/2} \quad (36)$$

where

$$a = \frac{\overline{\phi^2}}{(2\pi\mu)^2} \quad (37)$$

$$\frac{N^+}{B_{IF}} = e^{-\rho} \left[\frac{1 + 2 a \rho}{48 \pi \rho} \right]^{1/2} \quad (38)$$

Predictions of threshold performance using the Rice-Ridgeway criteria have shown that there is a noticeable improvement in the comparison between the theoretical and experimental curves when the click-noise due to modulation is taken into account. Figure 1 shows the results of this comparison. To summarize, the equation used to predict S/N behavior for the case of sinusoidal modulation and using the Rice-Ridgeway criteria is:

$$S_O/N_O = \frac{3/2 \rho \frac{B_{IF}}{f_a} \left[\frac{\Delta}{f_a} \right]^2}{-12\rho \left[\frac{B_{IF} B_D}{f_a^2} \right] \log^{-1} (.434 \rho + .788) + c} \quad (39)$$

For the case of a Gaussian noise type signal the equivalent expression is:

$$S_O/N_O = \frac{3/2 \rho \frac{B_{IF}}{f_a} \left[\frac{\Delta f}{f_a} \right]^2}{12 \rho \left[\frac{B_{IF} B_D}{f_a^2} \right] e^{-\rho} \left[\frac{1 + 2 a \rho}{48 \pi \rho} \right]^{1/2} + c} \quad (40)$$

When sinusoidal modulation is used, the increase in the number of clicks/second can be shown by the ratio:

$$\frac{N^+ \text{ for } A = 0}{N^+ \text{ for } A \neq 0} \approx 2 \sqrt{3} \left(\frac{\rho}{\pi} \right)^{1/2} + e^{-a\rho} I_0(a\rho) \quad (41)$$

It is concluded that the contribution of modulation to click noise is significant below the "knee" of the $(S/N)_0$ versus (Signal Power_{in}) curve. From Figure 1 it can be seen that the predicted curve for the case where $A \neq 0$ (Equation 39) is considerably closer to the measured data than the curve for the unmodulated case. Figure 2 shows that the predicted curve for no modulation gives a lower value for threshold than the measured data. The theoretical curve for sinusoidal modulation gives a very accurate prediction of threshold and is also closer to the measured data below threshold.